

Economy & Door Switch Striplights

Models: **SL-35** and **SL-60**

Installation Instructions:



We recommend the use of a registered electrician for installation.

IMPORTANT:

Isolate power supply before installation.

Connect Phase wire to L

Connect Neutral wire to N

Double insulated, do not earth

220V-240V, 50Hz

- This fitting must always be securely mounted to a flat surface. Entire body edge of fitting must rest against mounting surface, do not overhang, bridge or project any portion of the body so that access to any part of the body interior is allowed. If this is not possible, then mount via the use of a non-conductive backing panel.

- Do not mount this fitting directly onto any metallic or conductive surface.
- Keep lamp 50mm clear of adjacent surfaces.
- Maintain clearances in damp areas with respect of wiring rules.


Installation Position:

Position of the striplight will be determined by -

- Best location for light distribution, Horizontal at top or Vertical at side.
- Convenience and safety, so the light fitting does not become a nuisance or a hazard.

DS- Door Switch models

- Consider configuration of door/frame to decide if the Actuator should be used.



Included:
Optional use Actuator bracket

SL-35 Fitting Specification

LED ONLY 7W MAX.

L = 395mm, W = 34mm, H = 60mm



SL-60 Fitting Specification

LED ONLY 10W MAX.

L = 595mm, W = 34mm, H = 60mm



IMPORTANT: Lamp removal

